

TEMPEST-BAT300

URFOG battery fog generator

Multiple inputs and outputs

Up to 100 m3 without visibility

6 months of autonomy

Reduced size



URFOG

Fog generator

Battery powered

Generates 100 m3 of fog with zero visibility in 60"

6 months of autonomy

LED visual signaling

Multiple fault outputs

Allows external power supply from alarm center or 12V1.5A power supply

Adjustable trigger time

Total launching time 2 min

Total launching volume 200 m3

Includes batteries with higher current capacity

White colour

Reduced dimensions 300 (H) x 200 (W) x 150 (D) mm

Specifications

Brand	URFOG
Fog coverage	300 m3 (1 visibility meter) 100 m3 (zero visibility)
Fog Dispensing Time	2s - test 15s - 25m3 30s - 50m3 60s - 100m3
Total Dispensing Time	2 minutes+ 1 extra shot test
Delay time after triggering	Firing of 2s - 1 minute Firing of 15s - 5 minutes Firing of 30s - 10 minutes Firing of 60s - 20 minutes
Total Quantity Dispensed	600 m3 (1 visibility meter) 200m3 (zero visibility)
Cartridge capacity	0.125 L
Refill method	Easy to install cartridge
Reaction Time	200ms
Inputs	3 wired inputs: Arming, Triggering and PIR/Panic
Outputs	3 wired outputs (max 16V) - 50mA): Fault, Fluid and low battery
Power	High current capacity batteries 2x 12V-9Ah External power supply: 10-16V / 0.35-1.5A
Battery autonomy	Up to 6 months
Consumption	Low power mode < 3mW Always on mode 1.2W
Dimensions	300 (H) x 200 (W) x 150 (D) mm
Weight	7.6 Kg with battery 1.9 kg without battery
Installation type	Vertical