



WWW.SECURITYSYSTEMS.NO

SAFIRE BA609-HAC



SAFIRE UTP passive transceiver - Optimized for HDTV I / HDCVI / AHD - 1 video channel - Passive, connector of 2 pins - Range: 200 ~ 400 m - 2 units | Quick connection

- Safire
- Balun (transceiver)
- Optimized for HD video: HDTV I / HDCVI / AHD
- 1 channel
- Passive
- BNC/UTP 2 pins
- Video (no audio)
- Maximum reach HDTV I 250/250/100/100 m (720p/1080p/4 Mpx/4 K), HDCVI 400/250/200/200 m (720p/1080p/4 Mpx/4K) and AHD 350/200/200 m (720p/1080p/4 Mpx)
- 2 units (transmitter and receiver)
- Quick connection